

-17-

WHAT IS CLAIMED IS:

5 1. A radio frequency tag, comprising:
a threshold voltage generator coupled to a local
power supply and operable to generate a threshold voltage
signal on a threshold voltage generator output; and
a comparator having a first comparator input coupled
to an antenna to accept a received signal and a second
10 comparator input coupled to the threshold voltage
generator output to receive the threshold voltage signal,
the comparator powered by the local power supply and
operable to compare the received signal to the threshold
voltage signal and to generate a digital output based on
the comparison.

15 2. The radio frequency tag of claim 1, wherein the
comparator and the threshold voltage generator are
powered by only leakage current from the local power
supply.

20 3. The radio frequency tag of claim 1, wherein the
comparator and the threshold voltage generator are
powered by less than four microamps of current from the
local power supply.

25 4. The radio frequency tag of claim 1, wherein a
power consumption of the comparator is approximately
three microamps.

30 5. The radio frequency tag of claim 1, wherein a
power consumption of the threshold voltage generator is
less than 1 microamp of current from the local power
supply.

-18-

6. The radio frequency tag of claim 1, wherein the local power supply is a battery power supply.

7. The radio frequency tag of claim 1, wherein the local power supply is a lithium coin cell battery.

8. The radio frequency tag of claim 1, wherein the radio tag receives communicated signals on a very low frequency (VLF) carrier signal.

9. The radio frequency tag of claim 1, wherein the radio tag receives communicated signals on a low frequency (LF) carrier signal.

10. The radio frequency tag of claim 1, wherein the comparator has a propagation delay of less than fifteen percent of a period of a carrier signal on which communicated signals are received such that at least seven digital outputs are generated for each period.

11. The radio frequency tag of claim 1, wherein the comparator has a propagation delay of approximately ten percent of a period of a carrier signal on which communicated signals are received such that at least ten digital outputs are generated for the received signal during each period.

12. The radio frequency tag of claim 1, wherein the comparator has a propagation delay of less than one microsecond.

5

10

20

25

30

064383.0115

93¹⁵

-19-

sub
a3
13. The radio frequency tag of claim 1, the threshold voltage generator comprising:

5 a first resistor coupled to the local power supply;
a second resistor coupled in series to the first
resistor, the second resistor further coupled to a
ground; and

the threshold voltage generator output coupled to a
connection between the first resistor and the second
resistor.

10 14. The radio frequency tag of claim 13, further
comprising:

15 a capacitor coupled to the connection between the
first resistor and the second resistor, the capacitor
further coupled to the ground, the capacitor operable to
maintain a substantially constant voltage on the
threshold voltage generator output.

20 15. The radio frequency tag of claim 1, wherein the
threshold voltage signal is less than 50 millivolts.

16. The radio frequency tag of claim 1, wherein the
threshold voltage signal is less than 500 millivolts.

sub
a4
25 17. The radio frequency tag of claim 1, wherein the
radio frequency tag has a range in excess of ten feet.

30 18. The radio frequency tag of claim 1, wherein the
radio frequency tag has a range in excess of 25 feet.

19. The radio frequency tag of claim 1, wherein the
radio frequency tag has a range in excess of 100 feet.

-20-

sub
94
20. The radio frequency tag of claim 1, wherein the radio frequency tag has a range in excess of 150 feet.

21. A method for demodulating a signal at a radio frequency tag, comprising:

accepting a received signal;

generating a threshold voltage signal less than 50 millivolts;

comparing the received signal with the threshold voltage signal; and

generating a digital output based on the comparison of the received signal to the threshold voltage signal.

22. The method of claim 21, further comprising providing a comparator to compare the received signal to the threshold voltage signal.

23. The method of claim 21, wherein the threshold voltage signal is less than 10 millivolts.

20
sub
95
24. The method of claim 21, further comprising generating the threshold voltage signal and comparing it to the received signal using only leakage current from a local power supply.

25. The method of claim 21, further comprising generating the threshold voltage signal and comparing it to the received signal using less than four microamps of current from a local power supply.

add
96